



## NADITBNC-FX

Female XLR cable end 110  $\Omega$  input - female BNC 75  $\Omega$  output.  
Interface balanced and coaxial lines.

### Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match impedances 110  $\Omega$  to 75  $\Omega$
- Match balanced to coaxial lines
- Simple to use, passive units

**Technical Information**

Product	
<b>Title</b>	NADITBNC-FX
<b>Connection Type</b>	Adapter
<b>Gender</b>	female

Electrical	
<b>Frequencyrange</b>	0.1 - 6 MHz
<b>Rated voltage</b>	$\leq 5 \text{ V p-p}$
<b>VSWR</b>	$< 1.1$
<b>Return loss</b>	$> 26.4 \text{ dB}$
<b>Insertion Loss</b>	$< 0.3 \text{ dB @ } 0.1 \text{ MHz to } 10 \text{ MHz}$

Mechanical	
<b>Wiresize</b>	